
PRODUCT DATA SHEET


ARC-NV-24V



Product Features

1. Silicagel material, high temperature resistance, yellowing resistance, can be used in outdoor harsh weather.
2. Good flexibility, good bending, easy modeling and anti pulling force.
3. Corrosion resistance, acid and alkali can be used in extremely harsh conditions.
4. Uniform illumination, no spot, light effect is soft.
5. High brightness chip LED, pure gold wire, pure copper packaging, good heat dissipation, high stability, long service time.
6. Lead free SMT process (RoHS), smooth solder joints, solid and reliable connection.

Structure Introduction



 Diagram

Dimension mm/inch

Length/Reel	Width	Height	Min. Cutting
1000/39.37	10/0.3937	4/0.1575	Every 50mm/1.968inch (14 LEDs)

 Data

Part Number	Working Voltage	Power (W/m)	Current (A/m)	LED Qty/m	CRI
ARC-NV-24V	24V	18W/m	0.6780A/m	280LEDs/m	90+

CCT (°K)	Luminous Efficiency	Lumen/m
(12W/m) 3000K	82.44 lm/W	858.2 lm/m
(6W/m) Red	10.89 lm/W	61.51 lm/m
(18W/m) 2500K	56.12 lm/W	913.1 lm/m

Note:

The lumen output value tolerance + -5% due to testing way.

The CCT will be + -200k tolerance.


Installation accessories

**A**


Straight entry end cap

**B**


Bottom entry end cap



1. Cut according to the required length.
The strip has a mark every 50cm. Cut at the mark position




2. At the end of the outlet line, the inside of the plug and the outside of the strip are coated with special silica gel adhesive, and then put into the lamp band and use after 30 minutes.




Need outlet: penetrate wire into the plug hole to the other end of the plug.

Installation accessories




Weld wire through the plug on FPC, positive welding on(+),negative welding on(-)



At the end of the outlet line, the inside of the plug and the outside of the strip are coated with special silica gel adhesive, and then put into the lamp band and use after 30 minutes.

Wiring Diagram Application



Packaging

50m reel



Carton packaging




5m reel+Anti-electrostatic bag+Carton packaging




Attention

1. This product uses low voltage DC power supply, must use AC-DC switch. Use the power supply after voltage conversion! It is strictly forbidden to directly connect the LED light bar with AC 110V or AC 220V AC mains voltage connection, otherwise it will damage strip, and may cause a safety accident!




2. Bending direction requirements: Bending neon strip is required to bend along the upper and lower directions of the cross section, bending in the left and right directions of the cross section or seriously twisting will damage the strip.



3. Minimum bending diameter: The minimum bending diameter of curved neon strip is not less than 50 mm, and the bending diameter is less than 50 mm, which will easily damage the strip. Left and right directions of the cross section or seriously twisting will damage the strip.

4. During installation and use, there is a possibility of soiling the light strip. You can use a cotton cloth, dip it in clean water or sprinkle it, and gently wipe the dirty location to clean it.
5. Do not touch the product by means of heavy knocking or hammering;
Do not pull the lamp belt forcefully to avoid breaking the FPC in the product;
Do not pull the power cord forcefully to avoid the disc falling off;
Pay attention to the wiring.

Angle



The light emitting side is facing Upwards, the Strip is folded in Half (As shown) The minimum radius is 50mm, The minimum Angle is 45°.



5m/Reel, The minimum bending Diameter is 100mm.

During installation and use, there is a possibility of soiling the light strip. You can use a cotton cloth, dip it in clean water or sprinkle it, and gently wipe the dirty location to clean it.

✓ Safety & Disclosures

1. Do not install the led strip in environment where excessive heat may occur.
2. Do not extend beyond the recommended maximum run length.
3. Only use copper wiring. Use wires rated for at least 176°F (80°C) and certified for use with external connection of electrical equipment.
4. Do not install IP20 LED strip products in outdoor / wet location environments.
5. Excessive handling, bending, and pressure may damage the product, voiding the warranty.
6. Improper wire selection and installation could overheat wires, and cause fire.
7. Do not connect directly to high voltage or AC power.
8. Installation must be in accordance with local and national electrical code regulations.
9. To ensure safety and correct installation, our strips are intended to be installed by a qualified, licensed electrician